



| Format     | H    | L   |
|------------|------|-----|
| UI 39x8    | 21.7 | 3.7 |
| UI 39x10.2 | 23.8 | 4.1 |
| UI 39x13.5 | 27.1 | 4.1 |
| UI 39x17   | 30.8 | 4   |
| UI 39x21   | 34.8 | 4   |

| Rev | Date | Modification | Dessiné | Visa |
|-----|------|--------------|---------|------|
| D   |      |              |         |      |
| C   |      |              |         |      |
| B   |      |              |         |      |
| A   |      |              |         |      |

|            | Ref   | Puissance | Primaire | Fusible | Secondaire | ta   |
|------------|-------|-----------|----------|---------|------------|------|
| UI 39x8    | 45037 | 10VA      | 115-230V | 125/63  | 2x6V       | 50/B |
|            | 45038 | 10VA      | 115-230V | 125/63  | 2x9V       | 50/B |
|            | 45039 | 10VA      | 115-230V | 125/63  | 2x12V      | 50/B |
|            | 45040 | 10VA      | 115-230V | 125/63  | 2x15V      | 50/B |
|            | 45041 | 10VA      | 115-230V | 125/63  | 2x18V      | 50/B |
|            | 45042 | 10VA      | 115-230V | 125/63  | 2x24V      | 50/B |
| UI 39x10.2 | 45043 | 14VA      | 115-230V | 160/80  | 2x6V       | 50/B |
|            | 45044 | 14VA      | 115-230V | 160/80  | 2x9V       | 50/B |
|            | 45045 | 14VA      | 115-230V | 160/80  | 2x12V      | 50/B |
|            | 45046 | 14VA      | 115-230V | 160/80  | 2x15V      | 50/B |
|            | 45047 | 14VA      | 115-230V | 160/80  | 2x18V      | 50/B |
|            | 45048 | 14VA      | 115-230V | 160/80  | 2x24V      | 50/B |
| UI 39x13.5 | 45049 | 18VA      | 115-230V | 200/100 | 2x6V       | 50/B |
|            | 45050 | 18VA      | 115-230V | 200/100 | 2x9V       | 50/B |
|            | 45051 | 18VA      | 115-230V | 200/100 | 2x12V      | 50/B |
|            | 45052 | 18VA      | 115-230V | 200/100 | 2x15V      | 50/B |
|            | 45053 | 18VA      | 115-230V | 200/100 | 2x18V      | 50/B |
|            | 45054 | 18VA      | 115-230V | 200/100 | 2x24V      | 50/B |
| UI 39x17   | 45055 | 24VA      | 115-230V | 250/125 | 2x6V       | 50/B |
|            | 45056 | 24VA      | 115-230V | 250/125 | 2x9V       | 50/B |
|            | 45057 | 24VA      | 115-230V | 250/125 | 2x12V      | 50/B |
|            | 45058 | 24VA      | 115-230V | 250/125 | 2x15V      | 50/B |
|            | 45059 | 24VA      | 115-230V | 250/125 | 2x18V      | 50/B |
|            | 45060 | 24VA      | 115-230V | 250/125 | 2x24V      | 50/B |
| UI 39x21   | 45061 | 30VA      | 115-230V | 315/160 | 2x6V       | 50/B |
|            | 45062 | 30VA      | 115-230V | 315/160 | 2x9V       | 50/B |
|            | 45063 | 30VA      | 115-230V | 315/160 | 2x12V      | 50/B |
|            | 45064 | 30VA      | 115-230V | 315/160 | 2x15V      | 50/B |
|            | 45065 | 30VA      | 115-230V | 315/160 | 2x18V      | 50/B |
|            | 45066 | 30VA      | 115-230V | 315/160 | 2x24V      | 50/B |

|                              |            |  |            |
|------------------------------|------------|--|------------|
| Finition:                    |            | Tolérances générales:  |            |
| Finition:                    |            | General tolerances:  |            |
| Ech:                         | Matière:   |  |            |
|                              | Material:  |  |            |
| Dessiné par:                 | ROUSSEL.Ch | DATE:  | 17/10/2003 |
|                              |            | VISA:  | J.P.M.     |
| <b>TRANSFORMATEURS UI 39</b> |            |  |            |
|                              |            | 22, Allée du clos des charmes<br>Z.A Les Portes de la Forêt<br>77090 COLLEGIEN<br>Tél: 01.60.37.55.55<br>Fax: 01.60.17.12.00 |            |
| <b>UI 39</b>                 |            |  |            |